



NSC VOICE EVACUATION SYSTEM MILO & BOX-500

EN 54-16 FEUERWEHR-SPRECHSTELLEN ERWEITERUNG

FP-8BE

ARTIKEL-NR.: S22055-08

FP-8BE- Tastaturerweiterung für die Feuerwehr-Systemsprechstelle S22055-00

PRODUKTBESCHREIBUNG

Die FP-8BE ist eine Erweiterungstastatur / Zonenerweiterung für die Feuerwehreinprechstelle FP-AC. FP-8BE hat acht mittels Software programmierbare Tasten zur Anwahl von 8 weiteren Zonen. An jede FP-AC (Feuerwehreinprechstelle) können bis zu 7 Erweiterungstastaturen angeschlossen werden. Der Anschluss der Erweiterungstastatur erfolgt über den an der FP-AC seitlich angebrachten Connect-Port.

HAUPTMERKMALE

- 8 mittels Software programmierbare Tasten
- Bis zu 7 Erweiterungstastaturen pro Gerät können miteinander verbunden werden
- Besetzt-Anzeige für aktive Zonen
- Stabiles Metallgehäuse
- Lokale Stromversorgung

TECHNISCHE DATEN

Tasten	8 x Zonenauswahl
Betriebsbedingungen	-5 °C bis +45 °C, 5 % bis 95 % relative Luftfeuchtigkeit (nicht kondensierend)
Farbe	Grau RAL 7016
Gewicht	0,85 kg
Abmessungen (BxHxT)	86 x 132 x 50 mm
Zubehör Tastaturerweiterung	1 x Erweiterungs-Anschlussadapter; 2 x 5 Kontakte männlich-männlich; 1 x Anschlussstück an FP-AC; 4 x Senkschraube (M4 x 8 mm)



NSC VOICE EVACUATION SYSTEM MILO & BOX-500

EN 54-16 VOICE ALARM PANEL EXTENSION

FP-8BE

ARTICLE-NO.: S22055-08

Button expansion keyboard for the
FP-AC Fire Panel S22055-00

PRODUCT DESCRIPTION

FP-8BE is an 8-button expansion keyboard to connect to the FP-AC Fire Panel. Each of the 8 buttons can be programmed to select 1 up to 8 zones.

Up to 8 expansion keyboards can be connected to each FP-AC Fire Panel. By adding up to 8 additional FP-8BE units, announcements can be made in up to 512 zones.

KEY FEATURES

- 8 software programmable buttons
- Up to 8 can be connected
- Busy zone indicators
- Metallic chassis that provides stability and protection against damage.

TECHNICAL DATA

Buttons	8 x zone selection
Operating Conditions	-5 °C to +45 °C 5% to 95% Relative Humidity (no condensation)
Enclosure	Grey RAL 7016
Weight	0,85 Kg
Dimensions (WxHxD)	86 x 132 x 50 mm
Accessories Keyboard extension	1 x extension connection adapter; 2 x 5 contacts male-male; 1 x connector to FP-AC; 4 x countersunk screw (M4 x 8 mm)



NSC Sicherheitstechnik GmbH, Lange Wand 3, D-33719 Bielefeld, Germany

19 / 0370-CPR-5162 / EN54-16:2008

Voice alarm control and indicating equipment of fire detection and fire alarm systems